

PRODUCT-DETAILS

S303P-K0.3

S303P-K0.3 Miniature Circuit Breaker - 3P - K - 0.3 A



General Information	
Extended Product Type	S303P-K0.3
Product ID	2CDS383001R0117
EAN	4016779078122
Catalog Description	S303P-K0.3 Miniature Circuit Breaker - 3P - K - 0.3 A
Long Description	The MCBs S300P series assures protection in industrial installations against overload and short circuits. This product is manufactured according to international IEC and UL standards, for the markets where it is required.

ABB EcoSolutions ABB EcoSolutions Yes

Circular Value	
Circular Design Principles Recyclability Rate	Design for Closing Resource Loops - Standard EN45555 - 90 $\%$
Sustainable Material Content	O %
Group Waste to Landfill Target	No non-hazardous waste is sent to a landfill
Improved Resource Efficiency for Customers	Product Efficiency - Product requires less energy to operate compared to similar product on market or older products from the same line

Offered with Extended Lifetime	Product Durability
Offered with Takeback Services	Take Back for Recycling
End of Life Instructions	9AKK108467A9801

Eco Transparency Environmental Product 9AKK108467A7130 Declaration - EPD

Technical	
Standards	CSA 22.2 No. 235 IEC/EN 60947-2 UL 1077
Tripping Characteristic	P
Rated Operational Voltage	acc. to IEC 60898-1 415 V AC acc. to IEC 60898-1 415 V acc. to IEC 60947-2 415 V AC
Operational Voltage	Maximum (Incl. Tolerance) 457 V AC Maximum 457 V AC Minimum 12 V AC Minimum 12 V DC
Rated Insulation Voltage (U_i)	acc. to IEC/EN 60664-1 500 \
Rated Impulse Withstand Voltage (U_{imp})	6 kV
Dielectric Test Voltage	50/60 Hz, 1 min: 2 k\
Input Voltage Type	AC/DC
Rated Current (I _n)	0.3 A
Rated Short-Circuit Capacity	(400 V) 25 kA
Rated Ultimate Short- Circuit Breaking Capacity (I _{cu})	(415 V AC) 100 kA (440 V AC) 100 kA (400 V) 100 kA
Rated Frequency (f)	50 H: 60 H: 50 60 H:
Power Loss	3.3 W at Rated Operating Conditions per Pole 1.1 W
Power Supply Connection	Arbitrary
Contact Position Indication	Red ON / Green OF
Electrical Endurance	20000 AC cycle
Mechanical Endurance	20000 cycle
Number of Poles	
Number of Protected Poles	
Overvoltage Category	IN .
Tightening Torque	2.8 N·n
Screw Terminal Type	Failsafe Bi-directional Cylinder-lift Termina
Actuator Marking	1/0
Actuator Material	Insulation Group II, Black, Sealable
Housing Material	Insulation Group I, RAL 703
Mounting on DIN Rail	TH35-15 (35 \times 15 mm Mounting Rail) acc. to IEC 60715 TH35-7.5 (35 \times 7.5 mm Mounting Rail) acc. to IEC 60715
Mounting Position	any

Recommended Screw	Pozidriv 2
Driver	
Accessories Available	Yes
Connecting Capacity	Busbar 10 / 10 mm²
	Flexible with Ferrule 0.75 25 mm ²
	Flexible 0.75 25 mm ²
	Flexible 0.75 25 mm ²
	Rigid 0.75 35 mm ²
	Stranded 0.75 35 mm²
Installation Size	acc. to DIN 43880 1
Wire Stripping Length	14 mm
Terminal Type	Screw Terminals

Environmental	
Ambient Air Temperature	Operation -40 +70 °C Storage -55 +70 °C
Degree of Protection	IP20 IP40 Enclosure with Cover IP40
Pollution Degree	3
Environmental Conditions	28 cycles with 55 °C / 90-96 % and 25 °C / 95-100 %
Resistance to Vibrations acc. to IEC 60068-2-6	5g, 20 cycles at 5 150 5 Hz with load 0.8 In
Resistance to Shock acc. to IEC 60068-2-27	25g 3 shocks 18 ms
RoHS Status	Following EU Directive 2011/65/EU
RoHS Information	9AKK107991A3220
REACH Declaration	9AKK107492A1906
Conflict Minerals Reporting Template (CMRT)	9AKK108468A3363

Technical UL/CSA	
Maximum Operating Voltage UL/CSA	125 V DC 480Y / 277 V AC 480Y/277 V AC
Interrupting Rating acc. to UL1077	(125 V DC) 10 kA (480Y / 277 V AC) 10 kA
Connecting Capacity UL/CSA	Busbar 18-8 AWG Conductor 18-4 AWG
Tightening Torque UL/CSA	18 in-lb

Dimensions	
Width in Number of Modular Spacings	3
Product Net Width	52.5 mm
Product Net Height	88 mm
Product Net Depth / Length	69 mm
Product Net Weight	0.372 kg
Pole Net Weight	0.124 kg
Built-In Depth (t ₂)	69 mm

Ordering	
Package Level 1 Units	box 1 piece
Package Level 1 Gross Weight	0.387 kg
E-Number (Finland)	3212453

Certificates and Declarations	
CB Certificate	2CDZ405000A1089 2CDZ405000A1093
CCA Certificate	2CDZ405000A1090 2CDZ405000A1094
CCC Certificate	2CDZ405000A1097 2CDZ405000A1098
Certification Agency	CSA IEC EN UL
CQC Certificate	2CDZ405000A1097 2CDZ405000A1098
CSA Certificate	2CDZ405000A1102
Declaration of Conformity - CE	9AKK107991A3220
Declaration of Conformity - UKCA	9AKK107992A8877
DNV GL Certificate	2CDZ405000A1155
EAC Certificate	2CDZ405000A1092 2CDZ405000A1096
NF Certificate	2CDZ405000A1144
RINA Certificate	2CDZ405000A1194
UL Certificate	2CDZ405000A1101
VDE Certificate	2CDZ405000A1191 2CDZ405000A1195

Installation	
Instructions and	2CDS207104P0002
Manuals	

Popular Downloads	
Data Sheet, Technical	9AKK107992A4964
Information	

Classifications			
ETIM 8	EC000042 - Miniature circuit breaker (MCB)		
ETIM 9	EC000042 - Miniature circuit breaker (MCB)		
WEEE Category	5. Small Equipment (No External Dimension More Than 50 cm)		
WEEE B2C / B2B	Business To Business		
CN8	8536 20 10		
UNSPSC	39121603		
eClass	V11.0 : 27141901		
IDEA Granular Category Code (IGCC)	4897 >> Miniature circuit breakers		
Object Classification	F		

Identifier	Accessories						
2CDS200912R0001 S2C-H6R Auxiliary Contact S2C-H6R 1 piece 2CDS200970R0001 S2C-H01 Auxiliary Contact S2C-H01 1 piece 2CDS200970R0002 S2C-H10 Auxiliary Contact S2C-H10 1 piece 2CDS200936R0001 S2C-H11L Auxiliary Contact S2C-H10L 1 piece 2CDS200936R0003 S2C-H20L Auxiliary Contact S2C-H02L 1 piece 2CDS200936R0003 S2C-H6-11R Auxiliary Contact S2C-H6-1R 1 piece 2CDS200946R0001 S2C-H6-11R Auxiliary Contact S2C-H6-1R 1 piece 2CDS200946R0003 S2C-H6-2R Auxiliary Contact S2C-H6-20R 1 piece 2CDS200946R0003 S2C-H6-02R Auxiliary Contact S2C-H6-20R 1 piece 2CDS2009946R0003 S2C-H6-02R Auxiliary Contact S2C-H6-20R 1 piece 2CDS2009980001 S2C-M2 Park Auxiliary Contact S2C-H6-20R 1 piece 2CSS20091R001 S2C-UA 24A C Undervoltage Release S2C-UA 24AC 1 piece 2CSS20091R002 S2C-UA 24A C Unde	Identifier	Description	Туре	Quantity			
2CDS200970R0001 S2C-H01 Auxiliary Contact S2C-H01 1 piece 2CDS20093R0002 S2C-H10 Auxiliary Contact S2C-H10 1 piece 2CDS200936R0001 S2C-H11L Auxiliary Contact S2C-H20L 1 piece 2CDS200936R0003 S2C-H20L Auxiliary Contact S2C-H20L 1 piece 2CDS200936R0003 S2C-H02L Auxiliary Contact S2C-H02L 1 piece 2CDS200946R0001 S2C-H6-1R Auxiliary Contact S2C-H6-1R 1 piece 2CDS200946R0002 S2C-H6-2CR Auxiliary Contact S2C-H6-02R 1 piece 2CDS200946R0003 S2C-H6-2CR Auxiliary Contact S2C-H6-02R 1 piece 2CDS2009980001 S2C-H3 Shunt Trip S2C-A1 1 piece 2CSS200911R0001 S2C-UA 12 DC Undervoltage Release S2C-UA 24 AC 1 piece 2CSS200911R0002 S2C-UA 24 AC Undervoltage Release S2C-UA 48 AC 1 piece 2CSS200911R0003 S2C-UA 24 AC Undervoltage Release S2C-UA 48 AC 1 piece 2CSS200911R0004 S2C-UA 230 AC Undervoltage Release S2C-UA 40 <th>2CDS200922R0001</th> <th>S2C-S/H6R Signal / Auxiliary Contact</th> <th>S2C-S/H6R</th> <th>1</th> <th>piece</th>	2CDS200922R0001	S2C-S/H6R Signal / Auxiliary Contact	S2C-S/H6R	1	piece		
Section	2CDS200912R0001	S2C-H6R Auxiliary Contact	S2C-H6R	1	piece		
2CDS200936R0001 S2C-H2IL Auxiliary Contact S2C-H2IL 1 piece 2CDS200936R0002 S2C-H20L Auxiliary Contact S2C-H20L 1 piece 2CDS200936R0003 S2C-H20L Auxiliary Contact S2C-H20L 1 piece 2CDS200946R0001 S2C-H6-11R Auxiliary Contact S2C-H6-11R 1 piece 2CDS200946R0002 S2C-H6-20R Auxiliary Contact S2C-H6-20R 1 piece 2CDS200946R0003 S2C-H6-20R Auxiliary Contact S2C-H6-20R 1 piece 2CDS200990R0003 S2C-H6-20R Auxiliary Contact S2C-H6-20R 1 piece 2CDS200909R0001 S2C-H3 Shunt Trip S2C-A1 1 piece 2CDS200990R0002 S2C-A2 Shunt Trip S2C-A2 1 piece 2CSS200911R0001 S2C-UA 12 DC Undervoltage Release S2C-UA 12 DC 1 piece 2CSS200911R0002 S2C-UA 24 CU Undervoltage Release S2C-UA 44 AC 1 piece 2CSS200911R0003 S2C-UA 24 AC Undervoltage Release S2C-UA 48 AC 1 piece 2CSS200911R0004 S2C-UA 24 AC Undervoltage Release S2C-UA 48 AC 1 piece 2CSS200911R0005 S2C-UA 240 CU Undervoltage Release S2C-UA 240 AC 1 piece 2CSS200911R0006 S2C-UA 400 AC Undervoltage Release S2C-UA 240 AC 1 piece 2CSS200911R0006 S2C-UA 400 AC Undervoltage Release S2C-UA 240 AC 1 piece 2CSS200911R0006 S2C-UA 24 DC Undervoltage Release S2C-UA 240 C 1 piece 2CSS200911R0007 S2C-UA 24 DC Undervoltage Release S2C-UA 24 DC 1 piece 2CSS200911R0009 S2C-UA 24 DC Undervoltage Release S2C-UA 24 DC 1 piece 2CSS200911R0009 S2C-UA 24 DC Undervoltage Release S2C-UA 24 DC 1 piece 2CSS200911R0010 S2C-UA 230 DC Undervoltage Release S2C-UA 24 DC 1 piece 2CSS200991R0013 S2C-CM2/3 Motor operating device S2C-CM2/3 1 piece 2CSS200999R0013 S2C-CM2/3 Motor operating device S2C-CM4 1 piece 2CSS200999R0014 S2C-SP Mechanical tripping device S2C-CM4 1 piece 2CSS200999R0015 S2C-SP Mechanical tripping device S2C-SP 1 piece 2CSS200999R0001 S2C-SP Mechanical tripping base S2C-SE-ST 1 piece 2CSS20099BR0001 S2C-SP Mechanical tripping base S2C-SE-ST	2CDS200970R0001	S2C-H01 Auxiliary Contact	S2C-H01	1	piece		
2CDS200936R0002 \$2C-H20L Auxiliary Contact \$2C-H20L 1 piece 2CDS200936R0003 \$2C-H02L Auxiliary Contact \$2C-H02L 1 piece 2CDS200946R0001 \$2C-H6-11R Auxiliary Contact \$2C-H6-11R 1 piece 2CDS200946R0002 \$2C-H6-20R Auxiliary Contact \$2C-H6-02R 1 piece 2CDS200946R0003 \$2C-H6-02R Auxiliary Contact \$2C-H6-02R 1 piece 2CDS20099R0001 \$2C-H6-02R Auxiliary Contact \$2C-H6-02R 1 piece 2CDS20099R0002 \$2C-A1 Shunt Trip \$2C-A1 1 piece 2CSS20091R0001 \$2C-UA 12 DC Undervoltage Release \$2C-UA 24 1 piece 2CSS20091R0002 \$2C-UA 24 AC Undervoltage Release \$2C-UA 24 AC 1 piece 2CSS20091R0003 \$2C-UA 24 AC Undervoltage Release \$2C-UA 24 AC 1 piece 2CSS20091R0003 \$2C-UA 24 AC Undervoltage Release \$2C-UA 24 AC 1 piece 2CSS20091R0004 \$2C-UA 230 AC Undervoltage Release \$2C-UA 230 1 piece 2CSS20	2CDS200970R0002	S2C-H10 Auxiliary Contact	S2C-H10	1	piece		
2CDS200936R0003 \$2C-H02L Auxiliary Contact \$2C-H02L 1 piece 2CDS200946R0001 \$2C-H6-11R Auxiliary Contact \$2C-H6-11R 1 piece 2CDS200946R0002 \$2C-H6-20R Auxiliary Contact \$2C-H6-20R 1 piece 2CDS200946R0003 \$2C-H6-20R Auxiliary Contact \$2C-H6-20R 1 piece 2CDS20099080001 \$2C-A1 Shunt Trip \$2C-A1 1 piece 2CDS200991R0001 \$2C-A2 Shunt Trip \$2C-A2 1 piece 2CSS200911R0001 \$2C-UA 12 DC Undervoltage Release \$2C-UA 12 DC 1 piece 2CSS200911R0002 \$2C-UA 24 AC Undervoltage Release \$2C-UA 24 AC 1 piece 2CSS200911R0003 \$2C-UA 48 AC Undervoltage Release \$2C-UA 24 AC 1 piece 2CSS200911R0004 \$2C-UA 230 AC Undervoltage Release \$2C-UA 230 1 piece 2CSS200911R0005 \$2C-UA 240 AC Undervoltage Release \$2C-UA 240 1 piece 2CSS200911R0006 \$2C-UA 240 C Undervoltage Release \$2C-UA 240 C 1 piece 2	2CDS200936R0001	S2C-H11L Auxiliary Contact	S2C-H11L	1	piece		
2CDS200946R0001 \$2C-H6-11R Auxiliary Contact \$2C-H6-12R 1 piece 2CDS200946R0002 \$2C-H6-20R Auxiliary Contact \$2C-H6-20R 1 piece 2CDS200946R0003 \$2C-H6-02R Auxiliary Contact \$2C-H6-02R 1 piece 2CDS20099R0001 \$2C-A1 Shunt Trip \$2C-A1 1 piece 2CDS20091R0002 \$2C-A2 Shunt Trip \$2C-A2 1 piece 2CSS200911R0001 \$2C-UA 12 DC Undervoltage Release \$2C-UA 12 DC 1 piece 2CSS200911R0002 \$2C-UA 24 AC Undervoltage Release \$2C-UA 48 AC 1 piece 2CSS200911R0003 \$2C-UA 48 AC Undervoltage Release \$2C-UA 48 AC 1 piece 2CSS200911R0004 \$2C-UA 230 AC Undervoltage Release \$2C-UA 230 AC Undervoltage Release \$2C-UA 230 AC 1 piece 2CSS200911R0005 \$2C-UA 400 AC Undervoltage Release \$2C-UA 400 AC AC Undervoltage Release \$2C-UA 400 AC Undervolta	2CDS200936R0002	S2C-H20L Auxiliary Contact	S2C-H20L	1	piece		
2CDS200946R0002 \$2C-H6-20R Auxiliary Contact \$2C-H6-20R 1 piece 2CDS200946R0003 \$2C-H6-02R Auxiliary Contact \$2C-H6-02R 1 piece 2CDS200909R0001 \$2C-A1 Shunt Trip \$2C-A1 1 piece 2CDS200909R0002 \$2C-A2 Shunt Trip \$2C-A2 1 piece 2CSS200911R0001 \$2C-UA 12 DC Undervoltage Release S2C-UA 12 DC 1 piece 2CSS200911R0002 \$2C-UA 24 AC Undervoltage Release S2C-UA 12 DC 1 piece 2CSS200911R0003 \$2C-UA 48 AC Undervoltage Release S2C-UA 24 AC 1 piece 2CSS200911R0004 \$2C-UA 240 CUndervoltage Release S2C-UA 240 1 piece 2CSS200911R0005 \$2C-UA 230 AC Undervoltage Release S2C-UA 230 1 piece 2CSS200911R0006 \$2C-UA 240 CUndervoltage Release S2C-UA 240 1 piece 2CSS200911R0007 \$2C-UA 24 DC Undervoltage Release S2C-UA 24 DC 1 piece 2CSS200911R0009 \$2C-UA 230 CUndervoltage Release S2C-UA 48 DC 1 piece 2CSS200911R0000 \$2C-UA 230 DC Undervoltage Release S2C-UA 230 1 piece	2CDS200936R0003	S2C-H02L Auxiliary Contact	S2C-H02L	1	piece		
2CDS200946R0003 S2C-H6-02R Auxiliary Contact S2C-H6-02R 1 piece 2CDS200909R0001 S2C-A1 Shunt Trip S2C-A1 1 piece 2CDS200909R0002 S2C-A2 Shunt Trip S2C-A2 1 piece 2CSS200911R0001 S2C-UA 12 DC Undervoltage Release S2C-UA 12 DC 1 piece 2CSS200911R0002 S2C-UA 24 AC Undervoltage Release S2C-UA 24 AC 1 piece 2CSS200911R0003 S2C-UA 48 AC Undervoltage Release S2C-UA 48 AC 1 piece 2CSS200911R0004 S2C-UA 230 AC Undervoltage Release S2C-UA 230 1 piece 2CSS200911R0005 S2C-UA 230 AC Undervoltage Release S2C-UA 230 1 piece 2CSS200911R0006 S2C-UA 400 AC Undervoltage Release S2C-UA 400 1 piece 2CSS200911R0007 S2C-UA 24 DC Undervoltage Release 1 piece 2CSS200911R0008 S2C-UA 24 BC Undervoltage Release S2C-UA 48 DC 1 piece 2CSS200911R0010 S2C-UA 230 DC Undervoltage Release S2C-UA 48 DC 1 piece 2CSS20	2CDS200946R0001	S2C-H6-11R Auxiliary Contact	S2C-H6-11R	1	piece		
2CDS200909R0001 S2C-A1 Shunt Trip S2C-A1 1 piece 2CDS200909R0002 S2C-A2 Shunt Trip S2C-A2 1 piece 2CSS200911R0001 S2C-UA 12 DC Undervoltage Release S2C-UA 12 DC 1 piece 2CSS200911R0002 S2C-UA 24 AC Undervoltage Release S2C-UA 24 AC 1 piece 2CSS200911R0003 S2C-UA 48 AC Undervoltage Release S2C-UA 48 AC 1 piece 2CSS200911R0004 S2C-UA 110 AC Undervoltage Release S2C-UA 230 AC Undervoltage Release S2C-UA 230 AC Undervoltage Release AC 1 piece 2CSS200911R0006 S2C-UA 240 AC Undervoltage Release S2C-UA 400 AC Undervoltage Release S2C-UA 400 AC Undervoltage Release S2C-UA 24 DC 1 piece 2CSS200911R0006 S2C-UA 400 AC Undervoltage Release S2C-UA 24 DC 1 piece 2CSS200911R0007 S2C-UA 48 DC Undervoltage Release S2C-UA 24 DC 1 piece 2CSS200911R0010 S2C-UA 230 DC Undervoltage Release S2C-UA 110 DC 1 piece 2CSS201997R0013 S2C-UA 230 DC Undervoltage Release S2C-UA 110 DC <t< td=""><td>2CDS200946R0002</td><td>S2C-H6-20R Auxiliary Contact</td><td>S2C-H6-20R</td><td>1</td><td>piece</td></t<>	2CDS200946R0002	S2C-H6-20R Auxiliary Contact	S2C-H6-20R	1	piece		
2CDS200909R0002 S2C-A2 Shunt Trip S2C-A2 1 piece 2CSS200911R0001 S2C-UA 12 DC Undervoltage Release S2C-UA 12 DC 1 piece 2CSS200911R0002 S2C-UA 24 AC Undervoltage Release S2C-UA 24 AC 1 piece 2CSS200911R0003 S2C-UA 48 AC Undervoltage Release S2C-UA 48 AC 1 piece 2CSS200911R0004 S2C-UA 110 AC Undervoltage Release S2C-UA 110 AC 1 piece 2CSS200911R0005 S2C-UA 230 AC Undervoltage Release S2C-UA 230 AC 1 piece 2CSS200911R0006 S2C-UA 400 AC Undervoltage Release S2C-UA 240 AC 1 piece 2CSS200911R0007 S2C-UA 24 DC Undervoltage Release S2C-UA 24 DC 1 piece 2CSS200911R0008 S2C-UA 48 DC Undervoltage Release S2C-UA 48 DC 1 piece 2CSS200911R0009 S2C-UA 230 DC Undervoltage Release S2C-UA 110 DC 1 piece 2CSS200911R0010 S2C-UA 230 DC Undervoltage Release S2C-UA 110 DC 1 piece 2CSS201997R0013 S2C-CM2/3 Motor operating device S2C-CM1 S2C-CM1 piece 2CSS203997R0013 S2C-CM2/3 Motor operating device S2C-CM4 1 piece	2CDS200946R0003	S2C-H6-02R Auxiliary Contact	S2C-H6-02R	1	piece		
2CSS200911R0001 S2C-UA 12 DC Undervoltage Release S2C-UA 12 DC 1 piece 2CSS200911R0002 S2C-UA 24 AC Undervoltage Release S2C-UA 24 AC 1 piece 2CSS200911R0003 S2C-UA 48 AC Undervoltage Release S2C-UA 48 AC 1 piece 2CSS200911R0004 S2C-UA 110 AC Undervoltage Release S2C-UA 230 AC Undervoltage Release AC 1 piece 2CSS200911R0005 S2C-UA 230 AC Undervoltage Release S2C-UA 230 AC S2C-UA 240 AC	2CDS200909R0001	S2C-A1 Shunt Trip	S2C-A1	1	piece		
2CSS200911R0002 S2C-UA 24 AC Undervoltage Release S2C-UA 24 AC 1 piece 2CSS200911R0003 S2C-UA 48 AC Undervoltage Release S2C-UA 48 AC 1 piece 2CSS200911R0004 S2C-UA 110 AC Undervoltage Release S2C-UA 110 AC 1 piece 2CSS200911R0005 S2C-UA 230 AC Undervoltage Release AC S2C-UA 230 AC Undervoltage Release S2C-UA 400 AC 1 piece 2CSS200911R0006 S2C-UA 400 AC Undervoltage Release S2C-UA 24 DC 1 piece 2CSS200911R0007 S2C-UA 24 DC Undervoltage Release S2C-UA 24 DC 1 piece 2CSS200911R0008 S2C-UA 48 DC Undervoltage Release S2C-UA 110 DC 1 piece 2CSS200911R0009 S2C-UA 230 DC Undervoltage Release S2C-UA 110 DC 1 piece 2CSS200911R0010 S2C-UA 230 DC Undervoltage Release S2C-UA 230 DC 1 piece 2CSS201997R0013 S2C-UA 230 MC Undervoltage Release S2C-UA 230 DC 1 piece 2CSS204997R0013 S2C-CM2/3 Motor operating device S2C-CM2/3 DC 1 piece 2CSS200998R0001 S2C-BP Mechanical tripping device S2C-CM4 DC 1 piece 2CSS200999R0001 S2C-SET Plug-in base S2C-SET D	2CDS200909R0002	S2C-A2 Shunt Trip	S2C-A2	1	piece		
2CSS200911R0003 S2C-UA 48 AC Undervoltage Release S2C-UA 48 AC 1 piece 2CSS200911R0004 S2C-UA 110 AC Undervoltage Release S2C-UA 110 AC 1 piece 2CSS200911R0005 S2C-UA 230 AC Undervoltage Release AC 1 piece 2CSS200911R0006 S2C-UA 400 AC Undervoltage Release S2C-UA 400 AC 1 piece 2CSS200911R0007 S2C-UA 24 DC Undervoltage Release S2C-UA 24 DC 1 piece 2CSS200911R0008 S2C-UA 24 DC Undervoltage Release S2C-UA 24 DC 1 piece 2CSS200911R0009 S2C-UA 230 DC Undervoltage Release S2C-UA 48 DC 1 piece 2CSS200911R0010 S2C-UA 230 DC Undervoltage Release S2C-UA 110 DC 1 piece 2CSS201997R0013 S2C-CM2 30 DC Undervoltage Release S2C-UA 110 DC 1 piece 2CSS204997R0013 S2C-CM2/3 Motor operating device S2C-CM1 1 piece 2CSS204997R0013 S2C-CM4 Motor operating device S2C-CM4 1 piece 2CSS200998R0001 S2C-BP Mechanical tripping device S2C-BP 1 piece 2CSS20099R0001 S2C-BP Mechanical tripping device S2C-BP 1 piece 2CSS20099R0001 <t< td=""><td>2CSS200911R0001</td><td>S2C-UA 12 DC Undervoltage Release</td><td>S2C-UA 12 DC</td><td>1</td><td>piece</td></t<>	2CSS200911R0001	S2C-UA 12 DC Undervoltage Release	S2C-UA 12 DC	1	piece		
2CSS200911R0004 S2C-UA 110 AC Undervoltage Release S2C-UA 110 AC 1 piece 2CSS200911R0005 S2C-UA 230 AC Undervoltage Release S2C-UA 230 AC Undervoltage Release 1 piece 2CSS200911R0006 S2C-UA 400 AC Undervoltage Release S2C-UA 400 AC Undervoltage Release S2C-UA 24 DC 1 piece 2CSS200911R0007 S2C-UA 24 DC Undervoltage Release S2C-UA 24 DC 1 piece 2CSS200911R0008 S2C-UA 48 DC Undervoltage Release S2C-UA 48 DC 1 piece 2CSS200911R0009 S2C-UA 110 DC Undervoltage Release S2C-UA 110 DC 1 piece 2CSS200911R0010 S2C-UA 230 DC Undervoltage Release S2C-UA 230 DC 1 piece 2CSS201997R0013 S2C-CM2/3 Motor operating device S2C-CM1 1 piece 2CSS204997R0013 S2C-CM2/3 Motor operating device S2C-CM4 1 piece 2CSS20099R0001 S2C-DH Mechanical Accessories S2C-DH 1 piece 2CSS20099R0001 S2C-BP Mechanical tripping device S2C-BP 1 piece 2CSS20099R0001 S2C-S2P H L L L L L L L L L L L L L L L L L L	2CSS200911R0002	S2C-UA 24 AC Undervoltage Release	S2C-UA 24 AC	1	piece		
2CSS200911R0005 S2C-UA 230 AC Undervoltage Release S2C-UA 230 AC Undervoltage Release S2C-UA 400 AC Undervoltage Release S2C-UA 24 DC Undervoltage Release S2C-UA 24 DC Undervoltage Release S2C-UA 24 DC Undervoltage Release S2C-UA 48 DC Undervoltage Release S2C-UA 110 DC Undervoltage Release DC UNDERVOLTAGE S2C-UA 230 DC Undervoltage Release S2C-UA 110 DC Undervoltage Release S2C-UA 230 DC UNDERVOLTAGE S2C-UA 230 DC Undervoltage Release S2C-UA 230 DC Undervoltage Release S2C-UA 24 DC	2CSS200911R0003	S2C-UA 48 AC Undervoltage Release	S2C-UA 48 AC	1	piece		
S2C-UA 230 AC Undervoltage Release AC 1 piece	2CSS200911R0004	S2C-UA 110 AC Undervoltage Release	S2C-UA 110 AC	1	piece		
S2C-UA 400 AC Undervoltage Release	2CSS200911R0005	S2C-UA 230 AC Undervoltage Release		1	piece		
2CSS200911R0008 S2C-UA 48 DC Undervoltage Release S2C-UA 48 DC 1 piece 2CSS200911R0009 S2C-UA 110 DC Undervoltage ReleaseS2C-UA 110 DC 1 piece 2CSS200911R0010 S2C-UA 230 DC Undervoltage Release DC S2C-UA 230 DC Undervoltage Release DC 1 piece 2CSS201997R0013 S2C-CM1 Motor operating device S2C-CM1 1 piece 2CSS203997R0013 S2C-CM2/3 Motor operating device S2C-CM2/3 1 piece 2CSS204997R0013 S2C-CM4 Motor operating device S2C-CM4 1 piece GHS2001901R0003 S2C-DH Mechanical Accessories S2C-DH 1 piece 2CSS200998R0001 S2C-BP Mechanical tripping device S2C-BP 1 piece 2CSS200999R0001 S2C-BP Mechanical tripping device S2C-BT 1 piece 2CDS200918R0001 S2C-NT Hand Operated Neutral S2C-NT 1 piece 2CCA880100R0001 CMS-100PS Sensor CMS-100PS 1 piece 2CCA880101R0001 CMS-101PS Sensor CMS-101PS 1 piece	2CSS200911R0006	S2C-UA 400 AC Undervoltage Release		1	piece		
2CSS200911R0009 S2C-UA 110 DC Undervoltage ReleaseS2C-UA 110 DC 1 piece 2CSS200911R0010 S2C-UA 230 DC Undervoltage Release S2C-UA 230 DC 1 piece 2CSS201997R0013 S2C-CM1 Motor operating device S2C-CM1 1 piece 2CSS203997R0013 S2C-CM2/3 Motor operating device S2C-CM2/3 1 piece 2CSS204997R0013 S2C-CM4 Motor operating device S2C-CM4 1 piece GHS2001901R0003 S2C-DH Mechanical Accessories S2C-DH 1 piece 2CSS200998R0001 S2C-BP Mechanical tripping device S2C-BP 1 piece 2CSS200999R0001 S2C-EST Plug-in base S2C-EST 1 piece 2CDS200918R0001 S2C-NT Hand Operated Neutral S2C-NT 1 piece 2CCA880100R0001 CMS-100PS Sensor CMS-100PS 1 piece 2CCA880101R0001 CMS-101PS Sensor CMS-101PS 1 piece	2CSS200911R0007	S2C-UA 24 DC Undervoltage Release	S2C-UA 24 DC	1	piece		
2CSS200911R0010 S2C-UA 230 DC Undervoltage Release S2C-UA 230 DC Undervoltage Release S2C-UA 230 DC Undervoltage Release DC 1 piece 2CSS201997R0013 S2C-CM1 Motor operating device S2C-CM2/3 1 piece 2CSS203997R0013 S2C-CM2/3 Motor operating device S2C-CM2/3 1 piece 2CSS204997R0013 S2C-CM4 Motor operating device S2C-CM4 1 piece GHS2001901R0003 S2C-DH Mechanical Accessories S2C-DH 1 piece 2CSS200998R0001 S2C-BP Mechanical tripping device S2C-BP 1 piece 2CSS200999R0001 S2C-EST Plug-in base S2C-EST 1 piece 2CDS200918R0001 S2C-NT Hand Operated Neutral S2C-NT 1 piece 2CCA880100R0001 CMS-100PS Sensor CMS-100PS 1 piece 2CCA880101R0001 CMS-101PS Sensor CMS-101PS 1 piece	2CSS200911R0008	S2C-UA 48 DC Undervoltage Release	S2C-UA 48 DC	1	piece		
2CSS20091R0010 S2C-UA 230 DC Undervoltage Release DC 1 piece 2CSS201997R0013 S2C-CM1 Motor operating device S2C-CM1 1 piece 2CSS203997R0013 S2C-CM2/3 Motor operating device S2C-CM2/3 1 piece 2CSS204997R0013 S2C-CM4 Motor operating device S2C-CM4 1 piece GHS2001901R0003 S2C-DH Mechanical Accessories S2C-DH 1 piece 2CSS200998R0001 S2C-BP Mechanical tripping device S2C-BP 1 piece 2CSS200999R0001 S2C-BF Plug-in base S2C-EST 1 piece 2CDS200918R0001 S2C-NT Hand Operated Neutral S2C-NT 1 piece 2CCA880100R0001 CMS-100PS Sensor CMS-100PS 1 piece 2CCA880101R0001 CMS-101PS Sensor CMS-101PS 1 piece	2CSS200911R0009	S2C-UA 110 DC Undervoltage Release	S2C-UA 110 DC	1	piece		
2CSS203997R0013 \$2C-CM2/3 Motor operating device \$2C-CM2/3 1 piece 2CSS204997R0013 \$2C-CM4 Motor operating device \$2C-CM4 1 piece GHS2001901R0003 \$2C-DH Mechanical Accessories \$2C-DH 1 piece 2CSS200998R0001 \$2C-BP Mechanical tripping device \$2C-BP 1 piece 2CSS200999R0001 \$2C-EST Plug-in base \$2C-EST 1 piece 2CDS200918R0001 \$2C-NT Hand Operated Neutral \$2C-NT 1 piece 2CCA880100R0001 CMS-100PS Sensor CMS-100PS 1 piece 2CCA880101R0001 CMS-101PS Sensor CMS-101PS 1 piece	2CSS200911R0010	S2C-UA 230 DC Undervoltage Release		1	piece		
2CSS204997R0013 S2C-CM4 Motor operating device S2C-CM4 1 piece GHS2001901R0003 S2C-DH Mechanical Accessories S2C-DH 1 piece 2CSS200998R0001 S2C-BP Mechanical tripping device S2C-BP 1 piece 2CSS200999R0001 S2C-EST Plug-in base S2C-EST 1 piece 2CDS200918R0001 S2C-NT Hand Operated Neutral S2C-NT 1 piece 2CCA880100R0001 CMS-100PS Sensor CMS-100PS 1 piece 2CCA880101R0001 CMS-101PS Sensor CMS-101PS 1 piece	2CSS201997R0013	S2C-CM1 Motor operating device	S2C-CM1	1	piece		
GHS2001901R0003 S2C-DH Mechanical Accessories S2C-DH 1 piece 2CSS20099R0001 S2C-BP Mechanical tripping device S2C-BP 1 piece 2CSS200999R0001 S2C-EST Plug-in base S2C-EST 1 piece 2CDS200918R0001 S2C-NT Hand Operated Neutral S2C-NT 1 piece 2CCA880100R0001 CMS-100PS Sensor CMS-100PS 1 piece 2CCA880101R0001 CMS-101PS Sensor CMS-101PS 1 piece	2CSS203997R0013	S2C-CM2/3 Motor operating device	S2C-CM2/3	1	piece		
2CSS200998R0001 S2C-BP Mechanical tripping device S2C-BP 1 piece 2CSS200999R0001 S2C-EST Plug-in base S2C-EST 1 piece 2CDS200918R0001 S2C-NT Hand Operated Neutral S2C-NT 1 piece 2CCA880100R0001 CMS-100PS Sensor CMS-100PS 1 piece 2CCA880101R0001 CMS-101PS Sensor CMS-101PS 1 piece	2CSS204997R0013	S2C-CM4 Motor operating device	S2C-CM4	1	piece		
2CSS200999R0001 S2C-EST Plug-in base S2C-EST 1 piece 2CDS200918R0001 S2C-NT Hand Operated Neutral S2C-NT 1 piece 2CCA880100R0001 CMS-100PS Sensor CMS-100PS 1 piece 2CCA880101R0001 CMS-101PS Sensor CMS-101PS 1 piece	GHS2001901R0003	S2C-DH Mechanical Accessories	S2C-DH	1	piece		
2CDS200918R0001 S2C-NT Hand Operated Neutral S2C-NT 1 piece 2CCA880100R0001 CMS-100PS Sensor CMS-100PS 1 piece 2CCA880101R0001 CMS-101PS Sensor CMS-101PS 1 piece	2CSS200998R0001	S2C-BP Mechanical tripping device	S2C-BP	1	piece		
2CCA880100R0001 CMS-100PS Sensor CMS-100PS 1 piece 2CCA880101R0001 CMS-101PS Sensor CMS-101PS 1 piece	2CSS200999R0001	S2C-EST Plug-in base	S2C-EST	1	piece		
2CCA880101R0001 CMS-101PS Sensor CMS-101PS 1 piece	2CDS200918R0001	S2C-NT Hand Operated Neutral	S2C-NT	1	piece		
·	2CCA880100R0001	CMS-100PS Sensor	CMS-100PS	1	piece		
2CCA880102R0001 CMS-102PS Sensor CMS-102PS 1 piece	2CCA880101R0001	CMS-101PS Sensor	CMS-101PS	1	piece		
	2CCA880102R0001	CMS-102PS Sensor	CMS-102PS	1	piece		

Categories

 $Low\ Voltage\ Products\ and\ Systems\ \rightarrow\ Modular\ DIN\ Rail\ Products\ \rightarrow\ Miniature\ Circuit\ Breakers\ MCBs\ \rightarrow\ Miniature\ Circuit\ Breakers\ MCBs$





