SM1P0650

MOTOR PROTECTION CIRCUIT BREAKER, IEC BREAKING CAPACITY ICU 100KA AT 400V, 4...6.5A

Product designation			Motor protective circuit breaker
Product type designation			SM1P
Electrical features			
Number of poles		nr.	3
Magnetic protection			yes
Thermal protection			yes
Phase failure detection			Yes
Rated insulation voltage Ui IEC/EN		V	690
Rated impulse withstand voltage Uimp		kV	6
Rated frequency		Hz	50/60
Thermal trip adjustment range			4…6.5
Rated current (In)		A	6.5
Magnetic tripping			13 x In
Total power dissipation		W	1.99
Operational short-circuit current breaking capacity (Ics) at AC			
	230V	kA	100
	400V	kA	100
	440V	kA	100
	500V	kA	100
	690V	kA	3
Maximum short-circuit current breaking capacity (Icu) at AC			
	230V	kA	100
	400V	kA	100
	440V	kA	100
	500V	kA	100
	690V	kA	3
Tripping class			10A
IEC Utilization category			A
Operations			
Mechanical life		cycles	100000
Electrical life		cycles	100000
Mechanical features			
Tightening torque for terminals			
	min	Nm	2.5
	max	Nm	3
	min	lbin	1.8
	max	lbin	2.2
Max number of wires simultaneously connectable		nr.	2
Conductor section			
AWG/Kcmil			
	min		16
	max		8
Flexible w/o lug conductor section			
	min	mm²	1
Flexible c/w lug conductor section			
	min	mm²	1
Flexible with insulated spade lug conductor section			
	min	mm²	1
Screwdriver			PH2
Power terminal protection according to IEC/EN 60529			IP20
Cable stripping lenght			
	main circuit	mm	1
Ambient conditions			
Temperature			
Operating temperature			
	min	°C	-20
	max	°C	60
Storage temperature			
	min	°C	-50
	max	°C	80
Compensation temperature			
	min	°C	-20
	max	°C	50
Max altitude		m	3000

SM1P0650

MOTOR PROTECTION CIRCUIT BREAKER, IEC BREAKING CAPACITY ICU 100KA AT 400V, 4...6.5A

Operating position			
	normal		Vertical plan
	allowable		Any
Fixing			Screw / DIN rail 35mm
Weight		g	350
UL technical data			
UL508 / UL60947-4-1 Manual Motor Controller - Short circuit current			
Motor Disconnect			
	at 240V	kA	30
	at 480V	kA	30
	at 600V	kA	30
	protection		100A class J
Group Motor Installation			
	at 240V	kA	30
	at 480V	kA	30
	at 600V	kA	30
	protection		100A class J
Tap Conductor Protection			
	at 480Y/277V	kA	50
	at 600Y/347V	kA	50
UL508 / UL 60947-4-1 Manual Self Protected Combination Motor Controller (Type E) Short circuit current			
	UL508 / UL 60947-4-1 Manual Self Protected Combination Motor Controller (Type E) Short-circuit cur	kA	50
	UL508 / UL 60947-4-1 Manual Self Protected Combination Motor Controller (Type E) Short-circuit cur	kA	50
	UL508 / UL 60947-4-1 Manual Self Protected Combination Motor Controller (Type E) Short-circuit cur	kA	50
Maximum UL/CSA horsepower ratings single-phase			
	at 110V-120V	hp	1/4
	at 220V-240V	hp	1/2
Maximum UL/CSA horsepower ratings three-phase, 3-pole			
	at 200V-208V	hp	1.5
	at 220V-240V	hp	1.5
	at 440V-480V	hp	3
	at 550V-600V	hp	5

Dimensions



Wiring diagrams

SM1P0650

MOTOR PROTECTION CIRCUIT BREAKER, IEC BREAKING CAPACITY ICU 100KA AT 400V, 4...6.5A



Certifications and compliance

Certifications

CSA C22.2 n° 14
IEC/EN 60947-1
IEC/EN 60947-2
IEC/EN 60947-4-1
UL508

Compliance

cULus
EAC

ETIM 6 classification